

SINLOON® 微波雷達感應LED燈泡系列
Microwave radar sensing LED Bulb

型號/Type: MLL-MB Series
E27/B22 3W - 12W

Feature (特性)

- Microwave body sensors. 微波雷達感應.
- Non switch touching. 無開關接觸點.
- Sensor distance 感測距離遠.
- Intelligent control. 智能控制.
- Strong anti-jamming capability. 抗干擾能力強.

Figure (外型)



Application (應用)

Lobbies (大堂), Stairs(樓梯), Hallways (走道), Corridors(走廊),
Balcony (陽台), Kitchen (廚房), Bathroom (洗手間),
House door(屋外門口), Night lamp (夜燈),Etc...(等等...)

Specification:

型號	功率	尺寸	電壓	顯色指數	色溫	光通量	安裝高度
Model No.	Power	Size (Φ*H)	Voltage	CRI	Color Temp.	Luminous	Installation
MB203	3W	Φ50*82mm	85V~265V	>80Ra	3000K/6000K	300lm	3-5M
MB205	5W	Φ60*100mm	85V~265V	>80Ra	3000K/6000K	460lm	3-5M
MB209	9W	Φ80*123mm	85V~265V	>80Ra	3000K/6000K	800lm	3-5M
MB212	12W	Φ95*145mm	85V~265V	>80Ra	3000K/6000K	1100lm	3-5M
Luminous tolerance:	±5%						
Voltage Frequency:	50/60Hz						

General Specification:

感應角度	Angle sensors:	150° ~170°
感應距離	Sensor distance:	3 ~ 10M
延時時間	Extension time:	<2-200s To choose
工作溫度	Temperature:	<20°C ~+60°C
波段頻率	Band frequency:	5.8GHz
燈頭類別	Lamp holder type:	E27/B22
功率因數	Power Factor:	>85
輸入電壓	Wide range mains voltage AC85V ~ 265V	50/60Hz

Dimension: (mm)

Model No.	High	Dim. (Φ)
MB203	82mm	50mm
MB205	100mm	60mm
MB209	123mm	80mm
MB212	145mm	95mm

Application Features:

- People entering the sensitive area of LED lights,
- Lights automatically turn on, leave LED lights sensing area,
- The first darken after a certain time, and then automatically turn off the lights.
- High light efficiency> 92LM / W, No spot, Have CE certification.

特點:

當有人進入感應區域範圍時,自動啟動亮燈功能,當人離開感應區域範圍後燈自動延時漸暗至熄滅止。